

**Mars DBA Switch Setting for Icon**  
*Highlighted settings are factory default*

**OPTION SWITCHES - AE2461 – 115Volt**

<b>SWITCH 1 &amp; 2</b> - Bill Direction	
1 WAY	1-ON/2-OFF
2 WAY	1-OFF/2-ON
4 WAY	<b>1-ON/2-ON</b>
<b>SWITCH 3</b> - Acceptance	
HIGH ACCEPTANCE	<b>3-OFF</b>
HIGH SECURITY	3-ON
<b>SWITCH 4, 5, 6</b> - \$1, \$2, \$5 Acceptance	
\$1 BILL ACCEPT	<b>4-ON - Accept</b> / 4-OFF - Reject
\$2 BILL ACCEPT	<b>5-ON - Accept</b> / 5-OFF - Reject
\$5 BILL ACCEPT	<b>6-ON - Accept</b> / 6-OFF - Reject
<b>SWITCH 7</b> - Pulse Switches	
1 PULSE PER DOLLAR	<b>7-OFF</b>
4 PULSES PER DOLLAR	7-ON
<b>SWITCH 8</b> - Enable Switches	
ALWAYS ENABLED	<b>8-OFF</b>
HARNESS ENABLED	8-ON

**OPTION SWITCHES - AE2661- 115Volt**

<b>SWITCH 1 &amp; 2</b> - Bill Direction	
1 WAY	1 -ON/2-OFF
2 WAY	1 -OFF/2-ON
4 WAY	<b>1-ON / 2-ON</b>
<b>SWITCH 3</b> - Acceptance	
HIGH ACCEPTANCE	<b>3-ON</b>
HIGH SECURITY	3-OFF
<b>SWITCH 4, 5</b> - \$2, \$20 Acceptance	
\$2 BILL ACCEPT	<b>4-OFF - Accept</b> / 4-ON - Reject
\$20 BILL ACCEPT	<b>4-OFF - Accept</b> / 4-ON - Reject
<b>SWITCH 6</b> - Enable Switches	
ALWAYS ENABLED	<b>6 - ON</b>
HARNESS ENABLED	6 - OFF
<b>SWITCH 7</b> - Pulse Switches	
1 PULSE PER DOLLAR	<b>7- OFF</b>
4 PULSES PER DOLLAR	7 - ON
<b>SWITCH 8</b> - Interfaces	
Gaming Interface	<b>8 - OFF</b>
Vending Interface	8 - ON